

INSTALLATION AND OPERATING INSTRUCTIONS

1. Set the Housecode dial on the POWERHORN to the same letter as your security system
2. If you want to control the POWERHORN from other types of X10 controllers, set the Unit Code dial on the POWERHORN to any unused number between 1 & 16.
3. Plug the POWERHORN into an AC outlet (not one that is controlled by a wall switch, in case the switch accidentally gets turned off).
4. To test the POWERHORN, trip your alarm system. The POWERHORN will sound for as long as the alarm in the security system console sounds, and then shut off a few seconds after you disarm the alarm.

WARNING: The POWERHORN is extremely loud. To avoid permanent hearing damage, do not stand too close to it when you trip the alarm.

5. To trip the POWERHORN from any X10 controller (if you hear a strange noise at night, for example): Press Unit Code-ON, then Unit Code-OFF, then Unit Code-ON, repeatedly. The POWERHORN will sound for as long as you keep pressing ON and OFF and will stop a few seconds after you stop pressing buttons. Or press All Lights On, then All Units Off, repeatedly. The POWERHORN will sound for as long as you keep pressing All Lights On, followed by All Units Off and will stop a few seconds after you stop pressing buttons.

FCC Statement

THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES. OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITIONS: (1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND (2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED, INCLUDING INTERFERENCE THAT MAY CAUSE UNDESIRE OPERATION.

NOTE: NO CHANGES OR MODIFICATIONS MAY BE MADE TO THE UNITS. ANY CHANGES MADE TO THE UNITS WILL VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

120 DAY LIMITED WARRANTY x10pro-usa.com (X10PRO-USA), a division of Authinx Inc., warrants this product to be free from defective material and workmanship for a period of 120 days from the original date of purchase at retail. X10PRO-USA agrees to repair or replace, at its sole discretion, a defective product if returned to X10PRO-USA within the warranty period and with proof of purchase. If service is required under this warranty:

Call 1-888-384-0969, visit www.x10pro-usa.com, or email support@x10pro-usa.com



The X10 Supervised Security System includes a Security Console with an automatic dialer that calls friends or relatives in the event of a break in. Accessories include battery powered Radio Frequency (RF) Door/Window Sensors, battery powered RF Motion Detectors, battery powered RF Water Level Detectors, and RF Keyfob Remote Controls for arming and disarming the system. All sensors and remotes incorporate random digital security coding.

The system can be configured with any combination of the following items:

- Up to 16* Wireless Keyfob Security Remotes with arm/disarm and panic functions, and buttons to control security lights in and around the home.
- Up to 16* Wireless Water Level Detectors.
- Up to 30* magnetic switch operated Wireless Door/Window Sensors.
- Up to 30* Wireless PIR Motion Detectors.
- Optional X10 Home Automation modules such as plug-in lamp and appliance modules and wired-in replacement wall switches can be added to the system.

The Owner's Manual for the Security System describes the full installation process for the Security System, and should be referred to in addition to these instructions.

**Note: Door/Window Sensors, and Motion Detectors, may be added in any combination up to a total of 30, e.g. 15 Door/Window Sensors and 15 Motion Detectors, or any combination up to a total of 30. There are also 2 hard wired inputs, which are zones 31 and 32. Keyfob Security Remotes and Water Level Detectors can be added in any combination up to a total of 16, e.g. 8 Keyfobs and 8 Water Level Detectors*